

Appendix**T11****Selection Table**

T11: Conductor Resistances and Conductor Make-up (metric)

ÖLFLEX®

UNITRONIC®

ETHERLINE®

HITRONIC®

EPIC®

SKINTOP®

SILVYN®

FLEXIMARK®

ACCESSORIES

APPENDIX

Conductor Resistances and Conductor Make-up (metric)Conductor Resistances: for annealed-copper-conductors in single- and multicore cables $\geq 0.5 \text{ mm}^2$ acc. to DIN EN 60228 (VDE 0295)

Nominal cross-section in mm^2	Conductor resistance for 20°C for 1 km in Ω (maximum value)			
	of metal coated copper wire		of bare copper wire	
	Class 2	Class 5 + 6	Class 2	Class 5 + 6
0.08		250.0		243.0
0.14		142.0		138.0
0.25		82.0		79.0
0.34		59.0		57.0
0.5	36.7	40.1	36.0	39.0
0.75	24.8	26.7	24.5	26.0
1	18.2	20.0	18.1	19.5
1.5	12.2	13.7	12.1	13.3
2.5	7.56	8.21	7.41	7.98
4	4.70	5.09	4.61	4.95
6	3.11	3.39	3.08	3.30
10	1.84	1.95	1.83	1.91
16	1.16	1.24	1.15	1.21
25	0.734	0.795	0.727	0.780
35	0.529	0.565	0.524	0.554
50	0.391	0.393	0.387	0.386
70	0.270	0.277	0.268	0.272
95	0.195	0.210	0.193	0.206
120	0.154	0.164	0.153	0.161
150	0.126	0.132	0.124	0.129
185	0.100	0.108	0.0991	0.106
240	0.0762	0.0817	0.0754	0.0801
300	0.0607	0.0654	0.0601	0.0641
400	0.0475		0.0470	
500	0.0369		0.0366	
630	0.0286		0.0283	
800	0.0224		0.0221	
1000	0.0177		0.0176	

Examples of Conductor Make-up (metric)

Cross section in mm^2	Multi-Wire Strands	Multi-Wire Strands	Fine-Wire Strands	Super-Fine-Wire Strands			
				$\sim 18 \times 0.10$	$\sim 18 \times 0.1$	$\sim 36 \times 0.07$	$\sim 72 \times 0.05$
0.14				$\sim 14 \times 0.15$	$\sim 32 \times 0.10$	$\sim 32 \times 0.1$	$\sim 65 \times 0.07$
0.25				$\sim 19 \times 0.15$	$\sim 42 \times 0.10$	$\sim 42 \times 0.1$	$\sim 128 \times 0.05$
0.34		7×0.25		$\sim 12 \times 0.20$	$\sim 21 \times 0.15$	$\sim 48 \times 0.1$	$\sim 174 \times 0.05$
0.38		7×0.27		$\sim 16 \times 0.20$	$\sim 28 \times 0.15$	$\sim 64 \times 0.1$	$\sim 194 \times 0.05$
0.5	7×0.30	7×0.30		$\sim 24 \times 0.20$	$\sim 42 \times 0.15$	$\sim 96 \times 0.1$	$\sim 256 \times 0.05$
0.75	7×0.37	7×0.37		$\sim 32 \times 0.20$	$\sim 56 \times 0.15$	$\sim 128 \times 0.1$	$\sim 384 \times 0.05$
1.0	7×0.43	7×0.43		$\sim 30 \times 0.25$	$\sim 84 \times 0.15$	$\sim 192 \times 0.1$	$\sim 512 \times 0.05$
1.5	7×0.52	7×0.52		$\sim 50 \times 0.25$	$\sim 140 \times 0.15$	$\sim 320 \times 0.1$	$\sim 768 \times 0.05$
2.5	7×0.67	$\sim 19 \times 0.41$		$\sim 224 \times 0.15$	$\sim 512 \times 0.1$	$\sim 651 \times 0.07$	$\sim 1280 \times 0.05$
4	7×0.85	$\sim 19 \times 0.52$		$\sim 280 \times 0.40$	$\sim 768 \times 0.1$	$\sim 1040 \times 0.07$	
6	7×1.05	$\sim 19 \times 0.64$		$\sim 320 \times 0.20$	$\sim 1280 \times 0.1$	$\sim 1560 \times 0.07$	
10	7×1.35	$\sim 49 \times 0.51$		$\sim 320 \times 0.20$	$\sim 1920 \times 0.1$	$\sim 2600 \times 0.07$	
16	7×1.70	$\sim 49 \times 0.65$		$\sim 512 \times 0.20$			
25	7×2.13	$\sim 84 \times 0.62$		$\sim 800 \times 0.20$	$\sim 3200 \times 0.1$		
35	7×2.52	$\sim 133 \times 0.58$		$\sim 1120 \times 0.20$			
50	$\sim 19 \times 1.83$	$\sim 133 \times 0.69$		$\sim 400 \times 0.40$	$\sim 705 \times 0.30$		
70	$\sim 19 \times 2.17$	$\sim 189 \times 0.69$		$\sim 356 \times 0.50$	$\sim 990 \times 0.30$		
95	$\sim 19 \times 2.52$	$\sim 259 \times 0.69$		$\sim 485 \times 0.50$	$\sim 1340 \times 0.30$		
120	$\sim 37 \times 2.03$	$\sim 336 \times 0.67$		$\sim 614 \times 0.50$	$\sim 1690 \times 0.30$		
150	$\sim 37 \times 2.27$	$\sim 392 \times 0.69$		$\sim 765 \times 0.50$	$\sim 2123 \times 0.30$		
185	$\sim 37 \times 2.52$	$\sim 494 \times 0.69$		$\sim 944 \times 0.50$	$\sim 1470 \times 0.40$		
240	$\sim 37 \times 2.87$	$\sim 627 \times 0.70$		$\sim 1225 \times 0.50$	$\sim 1905 \times 0.40$		
300	$\sim 61 \times 2.50$	$\sim 790 \times 0.70$		$\sim 1530 \times 0.50$	$\sim 2385 \times 0.40$		
400	$\sim 61 \times 2.89$			$\sim 2035 \times 0.50$			
500	$\sim 61 \times 3.23$			$\sim 1768 \times 0.60$			
630	$\sim 91 \times 2.97$			$\sim 2286 \times 0.60$			

Visualisation:

Multi-Wire Strands	Fine-Wire Strands	Super-Fine-Wire Strands